

KMA-8240

Mixer Amplifier with MP3/FM Tuner/Bluetooth



Rated output power		240W
Output	Low impedance	4-16Ω
	70V	19Ω
	100V	39Ω
AUX output level		0.775V (0dBV)
Single Zone Output		100V
Input level	MIC 1,2,3	600Ω, 10-15mV (unbalanced)
	AUX 1,2	10KΩ, 200-470mV (unbalanced)
Extra Input		SD slot, USB slot, RCA connector
Frequency response		60Hz-15KHz (±3dB)
T.H.D.		<0.5% at 1KHz, 1/3 rated output power

KMA-8240

Mixer Amplifier with MP3/FM Tuner/Bluetooth



S/N ratio	MIC 1,2,3	$\geq 72\text{dB}$
	AUX 1,2	$\geq 85\text{dB}$
Tone	Bass	$\pm 10\text{dB}$ at 100Hz
	Treble	$\pm 10\text{dB}$ at 12KHz
Muting Function		MIC1 overrides other input signals at 0~30dB
Controls		Volume, tone/treble, mute, power
Protection		AC fuse, Overload, Short circuit, high temperature
		FUSE $\times 6\text{A}$
Cooling Fan		DC 12V FAN
LED indicator		AC: POWER, level: 2、4、6、8、10
Power supply		AC220~240V, 50-60Hz
Power consumption		350W

KMA-8240

Mixer Amplifier with MP3/FM Tuner/Bluetooth

Power cord	(3×0.75 mm ²)×1.5M (standard)
Product dimension (mm)	89(H)×483(W)×366(D)
Packaging dimension (mm)	185(H)×520(W)×435(D)
Net weight (kg)	13.8
Packaging weight (kg)	15.40

